

Overview

SCLASS™ Unified Power Systems are engineered to house FlexPower® power modules alongside SWH iSTAR™ access hardware in one compact listed enclosure.

This unit is a 12V and 24V DC dual voltage network managed access power system.

One M8 managed module provides eight access managed inputs capable of voltage or dry contact activation, and eight outputs programmable for failsafe / failsecure operation at either 12 or 24 VDC and managed by the integrated fire alarm interface circuit on the FPO. One D8 module provides eight auxiliary outputs and each output is configurable for 12 or 24VDC operation.


SCLASS enclosures are painted steel with removable backplate and include lock, two (2) keys and tamper switch.

System Features

- ◆ **FPO offline power supply**
 - 120 or 230 VAC input
 - 12 and 24 VDC outputs
 - On board Fire Alarm Interface
 - Continuous and resettable DC
- ◆ **Distributed outputs**
 - Eight auxiliary, fused at 3A each
 - Eight managed, fused at 3A each
- ◆ **Remote Monitoring & Control**
 - Live voltage / current reporting
 - Remote battery load testing
 - Output power cycling and abnormal operation alert
 - System / AC fault reporting
 - Email and SNMP trap notification
- ◆ **Lifetime Warranty**

Enclosure Features

- ◆ **Labor saving design**
 - Pre-wired power section
 - Pre-punched knockouts
 - Removeable backplate simplifies installs
 - Pre-defined hole pattern for power section
 - Access panels mount on threaded standoffs - no drilling required
- ◆ **Additional benefits**
 - Wire management room
 - 6.5" enclosure depth fits battery set
 - Tamper switch, lock, dual key set standard
 - Mounting hardware for access boards included



Ordering

FP0150-B100D8M8NL4E4S

Description


150W (12V & 24V) 8 managed outputs, networked



Specifications

Input Power	Input 120/230 VAC 50/60 Hz 170 Watts (1.41 Amps) Overload and short circuit protection Over temperature protection Polarized AC power supply disconnect
Output Power	4A@12V and 4A@24V DC, 150W maximum combined output power Outputs: Continuous (DC1) Resettable (DC2) 8 auxiliary outputs, fused at 3A each 8 managed control outputs, fused at 3A each 120 mV output voltage ripple System Efficiency: 88% System BTU Rating: 66 BTU/Hr
Battery Charging	Independent built-in 2A charger for sealed lead acid or gel type batteries Microprocessor dual rate charging of 12 or 24 V battery sets Charges up to 80Ah battery sets within UL limit Automatic switchover to standby battery when AC fails Zero voltage drop when switched over to battery backup
Supervision	AC Fail (form "C" contacts) System Fault (form "C" contacts) may be triggered by low/no battery, short to earth ground, power supply failure or blown fuse
Visual Indicators	AC input, DC1 and DC2 output System fault AC fault Short to earth ground Reverse battery polarity Fire Alarm Input activated B100: DC input, output and Fault M8: DC input, output and Fault D8: DC output
Regulatory Compliance LSP/SWH Joint Listing	UL294, UL603, UL1076, UL2610 ULC S318, ULC S319, CSA C22.2 #107.1, CSA C22.2 #60950 CE FCC Part 15, Subpart B CSFM Approved
Physical Dimensions	Enclosure: 24.00H x 20.00W x 6.50D in. (61.00 x 51.00 x 16.50 cm)
Access Mounting	SWH ULTRA or ULTRA SE Controllers

E4S backplate mounting pattern for power and access boards



Pattern	Slot	Fits AMAG
Blue	1	iSTAR ULTRA SE
Light Blue	1	iSTAR Ultra

lifesafetypower.com

(888) 577-2898
info1@lifesafetypower.com

Specifications subject to change without notice.

© 2022 LifeSafety Power. All rights reserved. LifeSafety Power and FlexPower are registered trademarks of LifeSafety Power. All other trademarks and copyrights are the property of their respective owners.
P01-777A 12/22

LifeSafety Power
10027 S. 51st Street, Suite 102
Phoenix, AZ 85044 USA